



AU-U22


Dante 2x2 CH USB-C/A Adapter

USB Audio Upgrade Instruction


Version: FW upgrade instruction_v1

Firmware Upgrade


This firmware enables 2x2 USB audio from previous 2x1 USB audio.




1. Disconnect the cat cable, and connect adapter to a Windows PC.
2. Extract the firmware upgrade packet and save on a PC.
3. Read the README file included in this upgrade package.
4. Run the SSS1700EEPROMDataConfigurationTool_9.9_2024.0322 upgrade tool.
5. Click on “Read EEPROM” and verify that the “USB product serial number” (version number) is 000000000000.




6. Click “Load file” and locate the firmware bin-file in the upgrade package named “AU-U22-DA_SSS1700-USB2X2-VID=0C76-PID=1700-24C02-202312251116.bin” Then click “Write EEPROM”.



7. Wait until upgrade is done.




8. Close the upgrade tool and click ok.




9. Power cycle the adapter by disconnecting USB cable from PC.

10. Verify that the USB "Microphone Properties" now shows support for 2 channel audio.



11. Some PC:s may need to clean USB device registry in order to detect the new support. If that is the case use the included "CleanUsbAudioRegistry_V1.3.2017.0317" tool. This can also be done manually if preferred. Run the tool and click "Clean".



12. Redo step 10 again to verify functionality.